

Exelon Enbeded DVR


SEARCH



To search for a particular section of recorded footage, press the **SEARCH** button.

To protect unauthorized viewing of footage, only ADMIN and MANAGER user levels can playback footage.

SEARCH : TIME SEARCH



Click the date that user wants to have the values changed.

The DVR uses a calendar and timeline search method for quick access to recorded footage.

The calendar displayed on the left shows the current month.


Days highlighted in yellow have recorded footage.

The timeline on the right shows a 24 hour status of all channels for the selected day.

The recorded time will be displayed with different color on each recording type.


- Panic : White
- Motion : Green
- Timer : Sky blue
- Alarm : Red

SEARCH



Drag the time bar with left mouse click.

Press **ENTER** to select the calendar and use the **CURSOR KEYS** to move to the required day.
As different days are selected, the timeline display also changes to show recorded footage on that day.
Press **ENTER** to choose the day and move to the timeline.



Click the
PANO(Thumbnail mode)
PLAY(Multi View)
buttons

Use the **CURSOR KEYS** to move the timeline cursor left or right to select the time segment required.
The currently selected time is displayed under the calendar.
Press **PLAY** to begin playback from the selected time.

SEARCH

SEARCH MODE : PANO

CH1	CH2	CH3
CH4	CH5	CH6
CH7	CH8	CH1 > x1 2010/07/07 BASE TIME +01:07:42

PANO(Thumb nail) :

Each Screen show s 3 hour data.

CH1 : 0~3 O'clock

CH2 : 3~6 O'clock

CH8: 21~24 O'clock

User can select different channels and playback with faster speed of up to x64.

SEARCH MODE : Multi Playback

CH1	CH2	CH3
CH4	CH5	CH6
CH7	CH8	CH1 > x2 2010/07/07 23:07:42

PLAY(Multi view):

The default playback mode is 16 screen display.

By pressing **DISPLAY** or using the **CHANNEL SELECTION** buttons, it is possible to display single screen or other multi screen formats in a similar way to the live display mode.

During playback, turning the **SHUTTLE WHEEL** steadily clockwise increases the playback speed by up to 64 times.



CH1	CH2	CH3
CH4	CH5	CH6
CH7	CH8	CH1 > x2 2010/07/07 23:07:42

Turning steadily counter-clockwise will reverse play by up to 64 times. When the **SHUTTLE WHEEL** is released, playback is paused.


If the **HOLD** button is pressed and released during **SHUTTLE WHEEL** operation, the last shuttle function is held, even if the wheel is released.

When playback is paused, the **JOG RING** can be used to accurately move the footage forward or backwards, frame by frame.

Playback speed and direction can also be controlled using the five playback buttons located under the jog wheel.

SEARCH

During playback, user can reserve the recorded data that needs to be archived.

Press  button at the time the archive is to be started. Then playback is stopped and menu below will appear.

INFORMATION

TAG

DATA1

FROM

2010/07/07 21:51:33

TO

2010/07/07 21:51:59

MEMO

INFO

117746 Kbytes

A/V CHANNEL

☒ CH1

☒ CH2

☒ CH3

☒ CH4

☒ CH5

☒ CH6

☒ CH7

☒ CH8

☒ CH9

☒ CH10

☒ CH11

☒ CH12

☒ CH13

☒ CH14

☒ CH15

☒ CH16

☒ LOG

RESERVE

CONTINUE

START

STOP

CLOSE

After inputting “TAG” name, press **START**. Then display is returned to playback.

Press  button again to end archiving. Then menu below will appear again.

INFORMATION

TAG

DATA1

FROM

2010/07/07 21:51:33

TO

2010/07/07 21:51:59

MEMO

INFO

117746 Kbytes

A/V CHANNEL

☒ CH1

☒ CH2

☒ CH3

☒ CH4

☒ CH5

☒ CH6

☒ CH7

☒ CH8

☒ CH9

☒ CH10

☒ CH11

☒ CH12

☒ CH13

☒ CH14

☒ CH15

☒ CH16

☒ LOG

RESERVE

CONTINUE

START

STOP

CLOSE

RESERVE: Press this to reserve current data.

CONTINUE: Press this to reserve more data. Then display will return to playback.

STOP: Make sure to press this button to reserve current data first. Then user can select RESERVE.

START: Press this to start the reserve.

CLOSE: Finish archiving.

Reserved data will be reserved on HDD. User can see the reserved data from “RESERVED DATA MANAGEMENT” on ARCHIVING menu

SEARCH

SEARCH

BY TIME

SEARCH

BY EVENT

◀◀ 2009 ▶▶

◀◀ APRIL ▶▶

◀ S

S

M

T

W

T

F

S

00

00

00

01

02

03

04

05

06

07

08

09

10

11

12

13

14

15

16

17

18

19

20

21

22

23

24

25

26

27

28

29

30

17 : 35 : 07

REFRESH

00 02 04 06 08 10 12 14 16 18 20 22

CH 1

CH 2

CH 3

CH 4

CH 5

CH 6

CH 7

CH 8

CH 9

CH 10

CH 11

CH 12

CH 13

CH 14

CH 15

CH 16

PANO

PLAY

CLOSE

To exit playback mode and return to the search screen to choose another time and date, press **RETURN**.

To exit the search screen and go back to live view, repeatedly press **RETURN**.

SEARCH : EVENT SEARCH

SEARCH

SEARCH BY TIME

SEARCH BY EVENT

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

FROM

2010/07/07 02:25:30 AM

TO

2010/07/08 04:27:40 PM

NEAREST

SEARCH

DATE/TIME

LOG

2010/07/08 04:27:40 PM

LOCAL LOG OFF: ARCHIVING : ADMIN

2010/07/08 04:20:32 PM

LOCAL LOG ON : ARCHIVING : ADMIN

2010/07/08 03:26:42 PM

TIME RECORDING OFF : #11

2010/07/08 03:26:42 PM

TIME RECORDING OFF : #10

2010/07/08 03:26:42 PM

TIME RECORDING OFF : #9

2010/07/08 03:26:42 PM

TIME RECORDING OFF : #8

PANO

PLAY

CLOSE

The DVR event log stores events such as motion and alarm activated recording, video loss, etc. To search for an event and playback the recorded footage, press the **SEARCH** button and log in as ADMIN with the default password of 1234.

SEARCH

BY TIME

SEARCH

BY EVENT

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

ON

FROM

2010/07/07 02:25:30 AM

TO

2010/07/08 04:27:40 PM

NEAREST

SEARCH

DATE/TIME

LOG

2010/07/08 04:27:40 PM

LOCAL LOG OFF: ARCHIVING : ADMIN

2010/07/08 04:20:32 PM

LOCAL LOG ON : ARCHIVING : ADMIN

2010/07/08 03:26:42 PM

TIME RECORDING OFF : #11

2010/07/08 03:26:42 PM

TIME RECORDING OFF : #10

2010/07/08 03:26:42 PM

TIME RECORDING OFF : #9

2010/07/08 03:26:42 PM


TIME RECORDING OFF : #8

PANO

PLAY

CLOSE

Click the **SEARCH BY EVENT** menu and select each desired channel and condition.

Then click the time with  button to change.

Click the **SEARCH** button.

SEARCH

SEARCH

BY TIME

SEARCH

BY EVENT

ON ☐

ON ☐

ON ☐

ON ☐

ON ☐

ON ☒

ON ☒

ON ☒

ON ☒

ON ☒

ON ☒

ON ☒

ON ☒

ON ☒

ON ☒

FROM 2010/07/07 02:25:30 AM

TO 2010/07/08 04:27:40 PM

NEAREST

SEARCH

DATE/TIME	LOG
2010/07/08 04:27:40 PM	LOCAL LOG OFF: ARCHIVING : ADMIN
2010/07/08 04:20:32 PM	LOCAL LOG ON : ARCHIVING : ADMIN
2010/07/08 03:26:42 PM	TIME RECORDING OFF : #11
2010/07/08 03:26:42 PM	TIME RECORDING OFF : #10
2010/07/08 03:26:42 PM	TIME RECORDING OFF : #9
2010/07/08 03:26:42 PM	TIME RECORDING OFF : #8

PANO

PLAY

CLOSE

Playback footage for a particular event, select the event from the list using the **CURSOR KEYS** and press **ENTER**.

CH1	CH2	CH3
CH4	CH5	CH6
CH7	CH8	

Playback resumes from the moment when the selected event occurred and continues until stopped by the operator. During event search playback, the **SHUTTLE WHEEL**, **JOG RING** and playback buttons can be used as normal. To stop playback and return to live view mode, repeatedly press **RETURN**.

ARCHIVING

NEW ARCHIVING

To archive recorded footage to USB memory stick or CD/DVD, press the **ARCHIVE** button.

To protect unauthorized viewing and distribution of footage, only the ADMIN user level can archive footage.

To login as ADMIN, enter the default password of 1234 and press **ENTER**.

ARCHIVING

NEW ARCHIVING

TAG

FROM 2010/07/07 02:56:00

TO 2010/07/07 22:56:00

RELEASE

QUERY

RESERVED DATA MANAGEMENT

SELECT DEVICE

NO DEVICE

ALL

CH1

CH2

CH3

CH4

CH5

CH6

CH7

CH8

CH9

CH10

CH11

CH12

CH13

CH14

CH15

CH16

LOG

LOG


TOTAL Size : 116736 Kbytes

RESERVE

RERN

CLOSE

Click each desired channel.

Then click the times with  button to change.

Click the **QUERY** menu.

Make sure to press QUERY first before selecting **BURN** or **RESERVE**.

Press RELEASE to reset after QUERY.

RESERVE: Press this after inputting the TAG name.

OR

BURN: Press this after inputting the TAG name. Then press **START** after menu below appears.

ARCHIVING

NEW ARCHIVING

TAG

FROM 2010/07/07 02:56:00

TO 2010/07/07 22:56:00

QUERY

RESERVED DATA MANAGEMENT

SELECT DEVICE

NO DEVICE

ALL

CH1

CH2

CH3

CH4

CH5

CH6

CH7

CH8

CH9

CH10

CH11

CH12

CH13

CH14

CH15

CH16

LOG

LOG

TOTAL Size : 116736 Kbytes

RESERVE

RERN

CLOSE

BURNING

ATG NAME

DATA3

DEVICE

USB MEM

BURNING TYPE

BURNING

WRITING...

55%

SAVE

CANCEL